

HIOKI

PHASE DETECTOR PD3129

NEW



Easy-to-read arrow indicator No-metal-contact design for the ultimate in safety



Include in visual reports

A green arrow indicates normal phase, which can be communicated in an easy-to-understand manner by including the phase detector in photographs used to document the proper completion of electrical work.



LED + clear audio for easy verification

The flashing phase sequence lamps, arrow LED, and tone let you easily and intuitively verify the phase sequence of three-phase power supplies.



Safe, no-metal-contact design

The no-metal-contact clips need only to be clipped to the outside of each wire's insulation, letting you carry out phase detection work safely.

Even more convenient in the field



Magnets for a more efficient workflow



The four magnets on the back of the phase detector allow it to be secured in place on distribution panels, significantly boosting work efficiency by freeing your hands for other tasks.

70 hours of use with two AA batteries



Two AA batteries deliver 70 hours of continuous use. This long service life means fewer troublesome battery changes. In addition, there's no need to carry spare batteries.

Battery check function



Normal operation



Low battery

A flashing lamp indicates when the batteries are low so that you can avoid having the detector turn off abruptly.

Auto power off



At power-on



Auto power off after 15 min.

To maximize battery life, the PD3129 turns off automatically 15 minutes after being turned on.

Choose from two models based on the type of power line

PD3129-10

For thick conductors

Measurable cable diameter

φ 7 mm to 40 mm
(0.28 in to 1.57 in)

Safety

CAT IV 600 V, CAT III 1000 V



Model : PHASE DETECTOR PD3129-10

Model No. (Order Code) (Note)
PD3129-10 (Large clips)

PD3129

For thin conductors

Measurable cable diameter

φ 2.4 mm to 17 mm
(0.09 in to 0.67 in)

Safety

CAT III 600 V



Model : PHASE DETECTOR PD3129

Model No. (Order Code) (Note)
PD3129

Specifications

	PD3129-10 (for thick conductors)	PD3129 (for thin conductors)
Functions	Phase detection (positive and negative)	
Voltage detection method	Electrostatic induction method	
Object to be connected	φ 7 mm (0.28 in) to 40 mm (1.57 in) of insulated wiring	φ 2.4 mm (0.09 in) to 17 mm (0.67 in) of insulated wiring
Voltage range	3-phase 70 to 1000V AC (continuous sine wave)	3-phase 70 to 600V AC (continuous sine wave)
Frequency range	45 Hz to 66 Hz	
Safety	CAT IV 600 V, CAT III 1000 V (Anticipated Transient Overvoltage of 8000 V)	CAT III 600V (Anticipated Transient Overvoltage of 6000 V)
Applicable standards	Safety: EN61010 / EMC : EN61326	
Phase indication	Positive: 4 LEDs lit in clockwise order and 3 short beeps, green arrow lights up Negative: 4 LEDs lit in counterclockwise order and one continuous beep	
Battery check function	Ready: ON lamp lights / Battery low: ON lamp blinks	
Auto power off	Auto shut off if no activity is detected after power is turned ON for 15 minutes	
Power supply	Two "AA" (R6P) size batteries; rated voltage: 3.0 V DC; maximum rated power: 300 mVA; continuous use: approx. 70 hours (standby)	
Dimensions	70 mm (2.76 in)W x 75 mm (2.95 in)H x 30 mm (1.18 in)D ; Cord length: 0.7 m (2.30 ft)	
Mass	240 g (8.5 oz) (including batteries)	200 g (7.1 oz) (including batteries)
Operating environment	Indoors, altitude up to 2000m Operating temperature: 0 to 40 °C (32 to 104°F), max. 80 % rh (no condensation) Storage Temperature: -20 to 60 °C (-4 to 140°F), max. 80% rh (no condensation)	
Accessories	Carrying case x 1, Strap x 1, R6P batteries x 2, Spiral tube x 1, Instruction manual x 1	

HIOKI
HIOKI E. E. CORPORATION

Contact:

Industrial Process Measurement, Inc.
3910 Park Avenue, Unit 7
Edison, NJ 08820
732-632-6400
support@instrumentation2000.com
<http://www.instrumentation2000.com>