

MICRO-OHMMETERS

200A Digital

Model 6292

Programmable test currents and test duration with data storage and report generation using included application software

NEW!

► SPECIFICATIONS

MODEL	6292
ELECTRICAL	
Test Current Range	Programmable from 5 to 200A (True DC)
Resistance Range	0.1μΩ to 2mΩ 2 to 200mΩ 200mΩ to 1Ω
Accuracy	± 1% of reading from 50μΩ to 1Ω
Resolution	0.1μΩ to 2mΩ < 0.1μΩ 2 to 200mΩ < 10μΩ 200mΩ to 1Ω < 1mΩ
Output Voltage	100VAC: 4.2V @ 200A 220VAC: 8.6V @ 200A
Max. Load Resistance	100VAC: 20mΩ @ 200A 220VAC: 42mΩ @ 200A
Measurement Method	Four-terminal, Kelvin-type
Adjustable Test Time	5 to 120 seconds or unlimited
Memory	Stores up to 8000 measurements
Power Supply	100 to 240VAC, 50/60Hz

Test results — **R = 100.0μΩ**
 Test current — **I_t = 142A I_g = 8.0A** — Ground current
TIME: 015/060s — Elapsed and total test times
 Date & time — **02/10/13 10:25**

► PRODUCT INCLUDES

Set of 20 ft Kelvin test leads w/C clamp, ground lead (green) with clamp, 5 ft USB cable, 110V US power cord and 12A fuse (5x20mm)

USB Stick

Quick start user guide, and USB stick supplied with DataView® software and user manual



► ACCESSORIES

► **Current Probe Model MR6292**
 Catalog #2129.86 (optional)



cover closed

► FEATURES

- Programmable test currents from 5 to 200A
- Programmable test duration from 5 to 120 sec
- BSG Ground Test with optional current probe
- Accurately measures low contact resistance with test currents up to 200A
- Measures resistances from 0.1μΩ to 1Ω
- Low resolution of 0.1μΩ
- Cooling system to improve the number of sequential tests that can be performed
- Backlit display
- Measures objects with both sides grounded
- Stores up to 8000 test results
- Direct printout of measurement results using DataView® software and a PC
- Rugged, light-weight and water-resistant case

CATALOG NO.

DESCRIPTION

2129.83 Micro-Ohmmeter Model 6292 (200A, manual and DataView® software)

Accessories (Optional)

2129.86 Current Probe Model MR6292

2129.87 Lead – Set of 2, 50 ft., Color-coded Kelvin Leads w/C-clamp