



The GDS-1000B Series digital storage oscilloscopes equip with 200/100/70 MHz : 2 Channel models; 100/70/50 MHz : 4 Channel models, that provide entry level users with diversified selections. The maximum real time sampling rate can be up to 1GSa/s. The robust functional performance makes the economical oscilloscope more colorful and allows entry level users to sumptuously enjoy the fun and value brought by test and measurement which is precisely the emerging mission of the test and measurement industry that GW Instek works relentlessly to achieve.

10M memory depth for each channel yields exquisite measurement results and allows each retrieved waveform to successfully reveal the details of signal. Engineers are often baffled by failing to retrieve signal details when measuring basic electric circuit signals. Now, GDS-1000B series oscilloscopes, with 10M memory depth for each channel, are capable to uncover all signal details.

7" 800 x 480 WVGA LCD display and the 256 color gradient display function together allow the GDS-1000B Series to distinctly display waveform details in gradients while measuring fast changing analog signals. Additionally, 50,000wfms/s waveform update rate helps engineers clearly understand the gradients of signal variations and easily identify the problem of transient signal variations.

1Mpts FFT signal display makes the frequency domain display function more delicate. Engineers can clearly observe the distributed details of frequency domain signals. Smooth and rapid response can even better locate where the problems are originated. Powerful FFT function realizes high efficient spectrum analysis measurement which is indispensable for technology and education arenas.

The GDS-1000B series provides serial bus analysis function with 10M long memory depth. Users can trigger, decode, and analyze frequently used I<sup>2</sup>C, SPI and UART serial bus and CAN/LIN bus, which is often used by automotive communications.

The GDS-1000B Series oscilloscopes provide the zero key function for vertical voltage scale adjustment, horizontal time scale adjustment and trigger level adjustment. When processing complicate waveform adjustment and observation, engineers often require the zero key function to start a new measurement, adjust waveform or reset trigger level. The zero key function can reduce time in turning control knobs that is a great benefit for engineers.

## GDS-1000B Series

### FEATURES

- 200/100/70 MHz : 2 Channel models ; 100/70/50 MHz : 4 Channel models
- 1GSa/s Maximum Sampling Rate
- 10M Maximum Memory Depth For Each Channel
- 7" 800 x 480 WVGA LCD Display
- 256 Color Gradient Display Function to Strengthen Waveform Performance
- 1Mpts FFT Frequency Domain Signal Display
- I<sup>2</sup>C/SPI/UART/CAN/LIN Serial Bus Trigger and Decoding Functions
- Zero Key Function For Horizontal Time, Vertical Voltage and Triggering



Front



Rear Panel

### APPLICATIONS

- Educational Market - General Purpose Instruction
- Industrial Sector - Fundamental R&D Measurement Applications

## SPECIFICATIONS

		GDS-1054B	GDS-1072B	GDS-1074B	GDS-1102B	GDS-1104B	GDS-1202B
VERTICAL	Channels	4	2 + Ext	4	2 + Ext	4	2 + Ext
	Bandwidth	DC~50MHz	DC~70MHz	DC~70MHz	DC~100MHz	DC~100MHz	DC~200MHz
VERTICAL	Rise Time	(-3dB) 7ns	(-3dB) 5ns	(-3dB) 5ns	(-3dB) 3.5ns	(-3dB) 3.5ns	(-3dB) 1.75ns
	Bandwidth Limit	20MHz	20MHz	20MHz	20MHz	20MHz	20MHz
VERTICAL	Vertical Sensitivity Resolution	8 bit : 1mV~10V/div					
	Input Coupling	AC, DC, GND					
VERTICAL	Input Impedance	1MΩ // 16pF approx.					
	DC Gain Accuracy*	±3%					
VERTICAL	Polarity	Normal & Invert					
	Maximum Input Voltage	300Vrms, CAT I (300Vrms CAT II with GTP-070B-4/100B-4 10:1 probe)					
VERTICAL	Offset Position Range	1mV/div : ±1.25V ; 2mV/div ~ 100mV/div : ±2.5V ; 200mV/div ~ 10V/div : ±125V					
	Waveform Signal Process	+ , - , × , ÷ , FFT, FFTrms, User Defined Expression ; FFT: 1Mpts; FFT: Spectral magnitude. Set FFT Vertical Scale to Linear RMS or dBV RMS ; FFT Window Display : Rectangular, Hamming, Handing, or Blackman-Harris					
TRIGGER	Source	CH1, CH2, CH3*, CH4*, Line, EXT** ; **two channel models only					
	Trigger Mode	Auto (supports Roll Mode for 100 ms/div and slower), Normal, Single Sequence					
TRIGGER	Trigger Type	Edge, Pulse Width, Video, Pulse Runt, Rise & Fall, Timeout, Alternate, Event-Delay(1~65535 events), Time-Delay(Duration, 4nS~10S)					
	Holdoff range	4ns to 10s					
TRIGGER	Coupling	AC, DC, LF rej., Hf rej., Noise rej.					
	Sensitivity	1div					
EXTERNAL TRIGGER	Range	±15V					
	Sensitivity	DC ~ 100MHz Approx. 100mV ; 100MHz ~ 200MHz Approx. 150mV					
EXTERNAL TRIGGER	Input Impedance	1MΩ ±3%~16pF					
	Time base Range	5ns/div ~ 100s/div (1-2-5 increments)					
HORIZONTAL	ROLL	100ms/div ~ 100s/div					
	Pre-trigger	10 div maximum					
HORIZONTAL	Post-trigger	2,000,000 div maximum					
	Timebase Accuracy	±50 ppm over any ≥1 ms time interval					
HORIZONTAL	Real Time Sample Rate	1GSa/s max.					
	Record Length	Max. 10Mpts					
HORIZONTAL	Acquisition Mode	Normal, Average, Peak Detect, Single					
	Peak Detection	2nS (typical)					
HORIZONTAL	Average	selectable from 2 to 256					
	X-Axis Input	Channel 1; Channel 3*(**four channel models only)					
X-Y MODE	Y-Axis Input	Channel 2; Channel 4*(**four channel models only)					
	Phase Shift	±3° at 100kHz					
CURSORS AND MEASUREMENT	Cursors	Amplitude, Time, Gating available; Unit : Seconds(s), Hz(1/s), Phase(degree), Ration(%)					
	Automatic Measurement	36 sets: Pk-Pk, Max, Min, Amplitude, High, Low, Mean, Cycle Mean, RMS, Cycle RMS, Area, Cycle Area, ROVShoot, FOVShoot, RPREShoot, FPREShoot, Frequency, Period, RiseTime, FallTime, +Width, -Width, Duty Cycle, +Pulses, -Pulses, +Edges, -Edges, FRR, FRF, FFR, FFF, LRR, LRF, LFR, LFF, Phase					
CURSORS AND MEASUREMENT	Cursors Measurement	Voltage difference between cursors (ΔV) Time ; difference between cursors (ΔT)					
	Auto Counter	6 digits, range from 2Hz minimum to the rated bandwidth					
CONTROL PANEL FUNCTION	Autoset	Single-button, automatic setup of all channels for vertical, horizontal and trigger systems, with undo Autoset					
	Save Setup	20set					
CONTROL PANEL FUNCTION	Save Waveform	24set					
	TFT LCD Type	7" TFT WVGA color display					
DISPLAY	Display Resolution	800 horizontal × 480 vertical pixels (WVGA)					
	Interpolation	Sin(x)/x					
DISPLAY	Waveform Display	Dots, vectors, variable persistence (16ms~4s), infinite persistence					
	Waveform Update Rate	50,000 waveforms per second, maximum					
DISPLAY	Display Graticule	8 x 10 divisions					
	Display Mode	YT, XY					
INTERFACE	USB Port	USB 2.0 High-speed host port x1, USB High-speed 2.0 device port x1					
	Ethernet Port(LAN)	RJ-45 connector, 10/100Mbps with HP Auto-MDIX (Only for 4 channel models.)					
INTERFACE	Go-NoGo BNC	5V Max/10mA TTL open collector output					
	Kensington Style Lock	Rear-panel security slot connects to standard kensington-style lock					
POWER SOURCE		AC 100V ~ 240V , 50Hz ~ 60Hz , Auto selection , Power consumption: 30 Watts					
MISCELLANEOUS	Multi-Language Menu	Available					
	Operation Environment	Temperature : 0°C ~ 50°C. Relative Humidity ≤ 80% at 40°C or below; ≤ 45% at 41°C ~ 50°C					
MISCELLANEOUS	Online Help	Available					
	DIMENSIONS & WEIGHT	380(W) × 208 (H) × 127.3(D)mm, Approx. 2.8kg					

The specifications apply when the GDS-1000B is powered on for at least 30 minutes under +20°C~+30°C.

Specifications subject to change without notice. DS-1000BGD2DH

### ORDERING INFORMATION

<b>GDS-1202B</b>	200MHz, 2 channels, Digital Storage Oscilloscope
<b>GDS-1104B</b>	100MHz, 4 channels, Digital Storage Oscilloscope
<b>GDS-1102B</b>	100MHz, 2 channels, Digital Storage Oscilloscope
<b>GDS-1074B</b>	70MHz, 4 channels, Digital Storage Oscilloscope
<b>GDS-1072B</b>	70MHz, 2 channels, Digital Storage Oscilloscope
<b>GDS-1054B</b>	50MHz, 4 channels, Digital Storage Oscilloscope

### ACCESSORIES

User manual x1, Power cord x1
GTP-200B-4 200MHz Passive Probe. Suitable for GDS-1202B
GTP-100B-4 100MHz Passive Probe. Suitable for GDS-1104B, GDS-1102B
GTP-070B-4 70MHz Passive Probe. Suitable for GDS-1074B, GDS-1072B, GDS-1054B

### OPTIONAL ASSESSORIES

<b>GDB-03</b>	Demo Board
<b>GTL-110</b>	Test lead, BNC to BNC heads
<b>GTL-246</b>	USB cable, USB 2.0 A-B type cable 4P, 1200mm
<b>GRA-426</b>	Rack Mount Kit
<b>GSC-008</b>	Soft carrying case
<b>GDP-025</b>	25MHz High voltage differential probe
<b>GDP-050</b>	50MHz High voltage differential probe
<b>GDP-100</b>	100MHz High voltage differential probe

### FREE DOWNLOAD

<b>Software</b>	OpenWave Software
<b>Driver</b>	USB Driver ; LabView Driver

**GW INSTEK**  
Simply Reliable

Contact:  
Industrial Process Measurement, Inc.  
3910 Park Avenue, Unit 7  
Edison, NJ 08820  
732-632-6400  
support@instrumentation2000.com  
http://www.instrumentation2000.com