

Multiple Output Linear D.C. Power Supply



The GPE-X323 series is cutting edge, economical linear DC Power supplies. The GPE-X323 series features output power from 192 to 217 watts, three independent isolated output channels (for GPE-3323), high resolution, low noise, high reliability, and compact size. The GPE-X323 series has a built-in digital panel control design to replace conventional control method. This unique design allows the GPE-X323 series linear DC power supply to provide users with more efficient functionalities, including set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage and current parameters. Additionally, output key light facilitates users in clearly reading the operational status of power supply.

Tracking Series and Parallel Operation

In addition to independent output channels, the GPE-X323 series provides tracking series and parallel operation (For GPE-2323/GPE-3323/GPE-4323). The series and parallel connections allow power supplies to output 32V/6A (Parallel Connection) and 64V/3A (Series Connection).



Internal connection for tracking Series and Parallel operation via control panel

Convenient Function


The GPE-X323 series has a built-in set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage/current parameters.



The key lock function prevent DUTs from unnecessary damages caused by mis-operation.

Remote I/O for output On/Off function

The GPE-X323 Series also provides the analog control (Remote I/O) function for external output On/Off control.



For controlling the output On/Off function through the specific pin assignment of remote control connector which is in rear panel.

GPE-X323 Series

FEATURES

- 1/2/3/4 Independent Isolated Output
- 4.3 Inch LCD Display
- Setting & Read Back Resolution 100mV/10mA (*1)
- Output On/off
- Analog Control (Remote I/O) For Output ON/OFF
- Set View Function For Checking an Original V/I Setting During Output On
- Key Lock Function
- Tracking Series And Parallel Operation
- Smart Cooling Fan Achieving Low Noise
- Optional European Jack Type Terminal



Front



Rear Panel

APPLICATIONS

- Laboratories and Educational Facilities
- Product Testing and Quality Assurance
- Service Operation and Post-Sales Support
- Product Development and Debugging

SPECIFICATIONS

		GPE-4323				GPE-3323			GPE-2323		GPE-1326
OUTPUT MODE	Number of Channel Voltage Current Tracking Series Voltage Tracking Parallel Current	CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH1	CH2	CH1
		0~32V	0~32V	0~5V	0~15V	0~32V	0~32V	5V	0~32V	0~32V	0~32V
		0~3A	0~3A	0~1A	0~1A	0~3A	0~3A	5A	0~3A	0~3A	0~6A
		0~64V		—		0~64V		—	0~64V		—
		0~6A				0~6A			0~6A		
CONSTANT VOLTAGE OPERATION	Line Regulation Load Regulation Ripple & Noise Recovery Time	$\leq 0.01\%+3\text{mV}$ $\leq 0.01\%+3\text{mV}$ (rating current $\leq 3\text{A}$); $\leq 0.02\%+5\text{mV}$ (rating current $> 3\text{A}$) $\leq 1\text{mVrms}$ (5Hz~1MHz) $\leq 100\mu\text{s}$ (50% Load Change, minimum load 0.5A)									
CONSTANT CURRENT OPERATION	Line Regulation Load Regulation Ripple & Noise	$\leq 0.2\%+3\text{mA}$ $\leq 0.2\%+3\text{mA}$ $\leq 3\text{mA}_{\text{rms}}$									
TRACKING OPERATION (CH1,CH2)	Tracking Error	$\leq 0.1\%+10\text{mV}$ of Master(0~32V) No Load , with Load add load regulation $\leq 100\text{mV}$									
	Parallel Regulation	Line : $\leq 0.01\%+3\text{mV}$ Load : $\leq 0.01\%+3\text{mV}$ (rating current $\leq 3\text{A}$); $\leq 0.02\%+5\text{mV}$ (rating current $>3\text{A}$)									
	Series Regulation	Line : $\leq 0.01\%+5\text{mV}$									
	Ripple & Noise	Load : $\leq 100\text{mV}$									
CH3 OPERATION FOR (GPE-3323)	Output Voltage Output Current Line Regulation Load Regulation Ripple & Noise	5.0V, $\pm 5\%$ 5A $\leq 3\text{mV}$ $\leq 5\text{mV}$ 1mVrms(5Hz~1MHz)									
METER	Voltage Resolution Current Resolution Setting Accuracy Readback Accuracy	100mV (*1) 10mA (*1) Voltage $\pm(0.1\%$ of reading +30mV); Current $\pm(0.3\%$ of reading +6mA) Voltage $\pm(0.1\%$ of reading +30mV); Current $\pm(0.3\%$ of reading +6mA)									
INSULATION	Chassis and Terminal Chassis and AC Cord	20M Ω or above (DC 500V) 30M Ω or above (DC 500V)									
ENVIRONMENT CONDITION	Operation Temp Storage Temp Operating Humidity Storage Humidity	0~40℃ -10~70℃ $\leq 80\%$ RH $\leq 70\%$ RH									
OTHER	Power Source Dimensions & Weight	AC100V/120V/220V $\pm 10\%$; 230V(+10%~-6%); 50/60Hz 210(W)x 155(H) x 306(D) mm ; Approx. 7kg									

Note : (*1) For a higher resolution (10mV/1mA), please follow the setting procedure of the user manual on p35.

When using a higher resolution, the current or voltage adjustment may be limited by the knob sensibility.

Specifications subject to change without notice. PE-x303CD1DH

ORDERING INFORMATION

GPE-1326 Single Channel, 192W Linear DC Power Supply
 GPE-2323 2 Channels, 192W Linear DC Power Supply
 GPE-3323 3 Channels, 217W Linear DC Power Supply
 GPE-4323 4 Channels, 212W Linear DC Power Supply

ACCESSORIES

User Manual (CD) x 1 ; Power Cord x 1
 GPE-1326 Test Lead GTL-104 x 1 ; GTL-105 x 1 ; or European GTL-204A x 1, GTL-203A x 1
 GPE-2323 Test Lead GTL-104 x 2 ; or European GTL-204A x 2,
 GPE-3323 Test Lead GTL-104 x 3 ; or European GTL-204A x 3
 GPE-4323 Test Lead GTL-104 x 2 ; GTL-105 x 2 or European GTL-204A x 2, GTL-203A x 2

GW INSTEK
 Simply Reliable

Contact:
 Industrial Process Measurement, Inc.
 3910 Park Avenue, Unit 7
 Edison, NJ 08820
 732-632-6400
 support@instrumentation2000.com
 http://www.instrumentation2000.com