

9200B 300A True RMS AC Mini Clamp Meter

True RMS provides better accuracy when measuring non-sinusoidal or noisy waveforms

Features:

- 4000 count display and simple 2 button operation
- Built-in non-contact AC voltage detector plus flashlight
- Data Hold
- Auto power off
- Low battery indicator
- CAT III 600V safety rating
- Includes wrist strap, 2 x 1.5V AAA batteries and case
- 1 year warranty



Applications:

Typically, when using a multimeter to measure current, you would have to “break the circuit” and place the meter in series with it, so that voltage and current would pass through it. A clamp meter allows you to easily measure current without breaking the circuit by clamping around a single conductor. This saves time and the circuit will not be damaged

Specifications

True RMS/Averaging	True RMS
Display Counts	4000
Clamp Size	1.14" (27mm)
Max cable diameter	300MCM
AC Current	0.01A to 300A
ACA Accuracy	±3%
NCV Detector	90 to 1000VAC (50/60Hz)
Safety Category	CAT III 600V
Dimensions / Weight	6 x 2.4 x 1.1 (152 x 60 x 28mm) / 4.7 oz. (134g)



Ordering Information:

9200B 300A True RMS AC Mini Clamp Meter
9200B-NIST 9200B Including Certificate of Traceability to N.I.S.T.

