

**THIS HIGH-VOLTAGE TESTER IS IDEAL FOR TESTING HIGH-VOLTAGE CABLES, SWITCHGEAR, HIGH-VOLTAGE TRANSFORMERS, ELECTRIC MOTORS AND SIMILAR EQUIPMENT.**



## **PORTABLE HIGH-VOLTAGE TESTER**

<b>MODEL</b> <b>DV-150VA-10V-01</b>	<b>SPECIFICATIONS</b>
<b>INPUT</b>	120 V 60 Hz Single-Phase
<b>OUTPUT</b>	Adjustable 0-15 kV dc @ 10 mA
<b>TRIP CURRENT</b>	Adjustable 3 -10 mA
<b>METERS</b>	One voltmeter 0-15 kV dc and one ammeter 0-10 mA Accuracy of both meters: $\pm 2\%$ of full scale
<b>INDICATORS</b>	5 Lights (Power-on, High-Voltage on, Off Zero Start, Fault and Line-Fault)
<b>CONTROLS</b>	Power on/off switch, fuse, reset-button, high-voltage on button, high-voltage off button, high-voltage adjust dial c/w zero start position, trip current adjust dial, safety device for incorrectly wired power outlet and safety interlock outlet c/w a plug.
<b>LEADS</b>	One input line-cord 2 meters (6 ft.) long), one high-voltage lead 3 meters (10 ft.) long and one ground lead 3 meters ( 10 ft.) long.
<b>SIZE</b>	48W x 41D x 25H cm (19W x 16D x 10H inches)
<b>WEIGHT</b>	18 kg (40 lb)

Contact:  
 Industrial Process Measurement, Inc.  
 3910 Park Avenue, Unit 7  
 Edison, NJ 08820  
 732-632-6400  
 support@instrumentation2000.com  
<http://www.instrumentation2000.com>