

9040 Phase Rotation Indicator



Technical Data

Features

- Large display to easily determine field rotation
- Indication for all three phases
- CAT III 600 V
- Included accessories: test leads and probes, alligator clips
- 2-Year Warranty

Phase Rotation Indicator for industrial applications

The Fluke 9040 Phase Rotation Indicator is a portable handheld instrument designed to detect the rotary field of three-phase systems. With three test leads, this rugged tester easily determines a clockwise or counterclockwise direction.

Specifications

Environmental

Operating temperature:
0 °C to +40 °C (32 °F to 104 °F)

Pollution degree: 2

Type of protection: IP 40

Mechanical specifications

Size (HxWxD):

124 mm x 61 mm x 27 mm
(4.9 in x 2.4 in x 1.1 in)

Weight: 200 g (0.44 lbs)

Safety specifications

Electrical safety:

IEC 61010/EN 61010,
IEC 61557-7/EN 61557-7

Maximum operating voltage (U_{me}): 690 V

Protection levels: CAT III 600 V to ground



Electrical specifications

Power supply: From unit under test

Determine rotary field direction

Nominal voltage: 40 to 690 V ac

Frequency range (f_n): 15 to 400 Hz

Current Pickup: 1 mA

Nominal test current (in per phase): 1 mA

Warranty: 2 years

Included

3 self-retaining test probes (black)

Alligator Clip

Users Manual

Ordering Information

Fluke-9040 Phase rotation
indicator

Fluke. Keeping your world
up and running.